



ATP-2000 SOFTWARE

Version v1.0.0

Release Notes

13-03082-200 AA

2020-11-13

www.grassvalley.com

Copyright and Trademark Notice

Grass Valley[®], GV[®] and the Grass Valley logo and/or any of the Grass Valley products listed in this document are trademarks or registered trademarks of GVBB Holdings SARL, Grass Valley USA, LLC, or one of its affiliates or subsidiaries. All other intellectual property rights are owned by GVBB Holdings SARL, Grass Valley USA, LLC, or one of its affiliates or subsidiaries. All third party intellectual property rights (including logos or icons) remain the property of their respective owners.

Copyright © 2020 - 2020 GVBB Holdings SARL and Grass Valley USA, LLC. All rights reserved. Specifications are subject to change without notice.

Product Patents

This product may be protected by one or more patents. For further information, please visit: www.grassvalley.com/patents/

Terms and Conditions

Please read the following terms and conditions carefully. By using ATP-2000 documentation, you agree to the following terms and conditions.

Grass Valley hereby grants permission and license to owners of ATP-2000s to use their product manuals for their own internal business use. Manuals for Grass Valley products may not be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, for any purpose unless specifically authorized in writing by Grass Valley.

A Grass Valley manual may have been revised to reflect changes made to the product during its manufacturing life. Thus, different versions of a manual may exist for any given product. Care should be taken to ensure that one obtains the proper manual version for a specific product serial number.

Information in this document is subject to change without notice and does not represent a commitment on the part of Grass Valley.

Warranty information is available from the Legal Terms and Conditions section of Grass Valley's website (www.grassvalley.com).

Warranty Policies

Warranty information is available from the Legal Terms and Conditions section of Grass Valley's website (www.grassvalley.com).

Title	ATP-2000 Software Version 1.0.0 Release Notes
Part Number	13-03082-200 AA
Revision	2020-11-13, 08:54

Related Documentation

You can obtain the latest product documentation from the Documentation Library section of Grass Valley's website (refer to www.grassvalley.com/docs/page/).

Use the following related documentation to configure an ATP-2000 and to better understand the available features. For first-time users, documentation should be read according to the Reading Order.

GV Part Number	Reading Order	Document Title
DS-PUB-2-0927A-EN	1	ATP-2000 Datasheet
13-03082-200	3	ATP-2000 Software Release Notes (this document)
13-03082-210	2	ATP-2000 Welcome Note
13-03082-230	4	ATP-2000 User Guide

toc

Table of Contents

Related Documentation	iii
1 ATP-2000 Software Release Notes	1
New Features, Enhancements, and Bug Fixes	2
ATP-2000 Software Version v1.0.0	2
Known Issues and Limitations	2
ATP-2000 Software Known Issues and Limitations	2
2 Installation and Network Requirements	3
Hardware Requirements	4
System Requirements	4
GV Orbit	4
Network Requirements	4
TCP/UDP Port Usage	4
Multicast and Unicast IP Ports	5
Default GV Orbit Domain Numbers	6
Software Component Compatibility	6
Supported Devices	7
Contact Us	8



ATP-2000 Software Release Notes

Chapter contents:

ATP-2000 Software Release Notes

<i>New Features, Enhancements, and Bug Fixes</i>	2
<i>ATP-2000 Software Version v1.0.0</i>	2
<i>Known Issues and Limitations</i>	2
<i>ATP-2000 Software Known Issues and Limitations</i>	2

The *ATP-2000 Software Release Notes* document lists new features and enhancements, along with any fixed bugs, as well as any known issues and limitations associated with the latest version of the ATP-2000 Advanced Touch Panel software.

ATP-2000 Software version 1.0.0 is a new release and the full software version number is:

v1.0.0-b4

This chapter lists [New Features, Enhancements, and Bug Fixes](#), on page 2, and [Known Issues and Limitations](#), on page 2.

New Features, Enhancements, and Bug Fixes

The following is a list of added ATP-2000 Software features and enhancements. The most recent items are marked with a star (★) symbol.

ATP-2000 Software Version v1.0.0

This is the first release.

Known Issues and Limitations

The following is a list of known issues and limitations associated with ATP-2000 Software release. The star (★) symbol indicates a new issue in ATP-2000 Software version 1.0.0.

ATP-2000 Software Known Issues and Limitations

- ★ [Ref. #UCCM-2209] **Double clicking radio button causes jump between two values:**
Use a *single* click to on a radio button on an ATP-2000 panel screen to switch from one value to another. Avoid double-clicking on radio buttons.

- ★ [Ref. #UCCM-2210] **Pressing 'Previous' in a Card List with no Card Selected:**
Do not press "Previous" in the card list when no card is selected. This causes the first card's control screen to be opened. Re-select card list navigation buttons to find desired card.

- ★ [Ref. #UCCM-2440] **Only XIP-3901-UDC-IP version 1.2.0 build 439 is supported in this first ATP-2000 Advanced Touch Panel release:**
There is no mechanism in place to handle any new or older versions of the XIP-3901-UDC-IP. Only the XIP-3901-UDC-IP version 1.2.0 build 439 is supported today.
The initial card to be supported is the XIP-3901-UDC-IP. And ATP-2000 software currently supports *only* the following **XIP-3901-UDC-IP** application software version:
XIP-3901-UDC-IP **version 1.2.0 build 439**
CAUTION: Use only this XIP-3901 application software version.
Support for other cards/versions will be added in future releases.

2

Installation and Network Requirements

Chapter contents:

Installation and Network Requirements

<i>Hardware Requirements</i>	4
<i>System Requirements</i>	4
<i>GV Orbit</i>	4
<i>Network Requirements</i>	4
<i>TCP/UDP Port Usage</i>	4
<i>Multicast and Unicast IP Ports</i>	5
<i>Default GV Orbit Domain Numbers</i>	6
<i>Software Component Compatibility</i>	6
<i>Supported Devices</i>	7

This section details the requirements that must be met prior to installing or upgrading software on an ATP-2000 Advanced Touch Panel from Grass Valley.

An ATP-2000 typically operates in a GV Orbit system with one or more GV Orbit servers and one or more GV Orbit Client PCs.

Hardware Requirements

The ATP-2000 software runs on an ATP-2000 Advanced Touch Panel.

Table 2-1: ATP-2000 Software Compatibility

Product Order Code	Compatible ATP-2000 Software Version	Comment
ATP-2000	v1.0.0	Initial variant of the ATP-2000 Advanced Touch Panel.

System Requirements

GV Orbit

For an ATP-2000 in a GV Orbit system, there are one or more GV Orbit servers, and one or more GV Orbit Client PCs each running a GV Orbit Client application. A working GV Orbit system is required.

Required GV Orbit server running GV Orbit software version:

GV Orbit v1.5 or later.

Network Requirements

An ATP-2000 must have network connectivity to the GV Orbit system and ideally connected to a network that supports multicast traffic (for auto-discovery of devices).

TCP/UDP Port Usage

The various communication protocols used in a GV Orbit system for talking to an ATP-2000 require specific IP ports. The following network IP ports are used:

Client PC Open Network Port Requirements

IP Port	Open Inbound	Open Outbound	Used by Application/Protocol
22	●		Reserve for future use.
80		●	ATP-2000 panel web page.
2050	●	●	Default RollCall comms port.
5951 5953 5955	●	●	Densité REST API
8000	●		ATP-2000 panel upgrade.
Multicast and Unicast	●	●	See Multicast and Unicast IP Ports , on page 5.

Multicast and Unicast IP Ports

Multicast and Unicast Port Usage and Domain ID

The IP ports required for communication between the GV Orbit Client, GV Orbit services running on a ATP-2000 server, and other Grass Valley devices that make use of a Domain ID, are derived from the value of the Domain ID and the number of participants on the Domain.

For each Domain there is:

- one multicast port required for each participant to a Domain; and
- two unicast ports are required.

Multicast and Unicast Port Formulas

The following formulas are used to calculate the required multicast and unicast port numbers.

$$\text{Discovery Multicast Port} = 7400 + (250 \times \text{Domain ID})$$

$$\text{Discovery Unicast Port} = 7400 + (250 \times \text{Domain ID}) + (2 \times \text{Participant ID}) + 10$$

$$\text{Data Unicast Port} = 7400 + (250 \times \text{Domain ID}) + (2 \times \text{Participant ID}) + 11$$

Note: Participant IDs are zero-based.

Ports and Default Domain IDs

Default Domain IDs are used by the GV Orbit Client and by the GV Orbit services running on a GV Orbit server. The IP ports used for default Domain IDs are described below; if using user-defined Domain IDs, use the formulas above to calculate the required IP port numbers.

The following network ports must be open inbound and outbound on PCs running the GV Orbit Client; recalculate if a different Domain ID is used, or if multiple projects that use the same Domain ID are open concurrently:

Multicast and Unicast Ports Used for Default Domain IDs

ATP-2000 Item	Default Domain ID	Multicast IP Port	Unicast IP Port	Comment
-	0	7400	7410 7411	Domain 0 used for ATP-2000 panel discovery.
Monitoring	100	32400	32410 32411	Used for communication with a GV Orbit server.
Note: These IP ports must be open inbound and outbound on client PCs.				

Note: When opening multiple projects on the same Domain at the same time, additional IP ports must be opened in accordance with the number of Domain Participants. Whilst the port numbers can be determined from the above formulas, the actual assignment of an IP port number to a Domain Participant is random.

Default GV Orbit Domain Numbers

A GV Orbit system communicates with various parts of its system and employs 'domains' to segregate its communications. Domains are specified with a Domain ID number (1 to 252; 0 is used for discovery). Domain numbers may be configured by the user as required as this may be necessary when you have more than one GV Orbit Server on the same network.

A new GV Orbit system uses default Domain IDs, described in the table below:

Default GV Orbit System Domain IDs

ATP-2000 Domain	Default Domain ID	Comment
System	0	Used for system auto-discovery.
Reserved	1 to 99	Reserved for Grass Valley engineering use only.
Monitoring	100	Monitoring traffic, also known as the 'Client Domain'.
IP Endpoint Routing	101	Control of IP Endpoints for signal routing.
Routing Topology	105	For future GV Orbit releases.
Log Server	110	Used by the LogServer service for RollCall-protocol devices.
Biometrics	201	For future GV Orbit releases.

Software Component Compatibility

ATP-2000 Advanced Touch Panel requires:

- GV Orbit server running GV Orbit software v1.5 or later.

Supported Devices

The ATP-2000 Advanced Touch Panel supports the ability to configure, control, and monitor parameters on IQ and Densité Grass Valley devices.

Table 2-2: ATP-2000 - Supported Devices

Card	Software Version	Comment
XIP-3901	XIP-3901-UDC-IP version 1.2.0 build 439	Ability to configure basic operational parameters for an XIP-3901 device.

Note: See documentation for the respective supported card/unit for more information. (Refer to www.grassvalley.com/docs/page/ and go to the required product web page for documentation.)



Grass Valley Technical Support

For technical assistance, contact our international support center, at 1-800-547-8949 (US and Canada) or +1-530-478-4148.

To obtain a local phone number for the support center nearest you, consult the Contact Us section of Grass Valley's website (www.grassvalley.com).

An online form for e-mail contact is also available from the website.

Corporate Head Office

Grass Valley
3499 Douglas-B.-Floreani
St-Laurent, Quebec H4S 2C6
Canada
Telephone: +1 514 333 1772
Fax: +1 514 333 9828
www.grassvalley.com